



# Power Box DS3 Sources

Universal linear power supply for up to 5 components & 1 turntable

Colour options: ● ●

- All-in-one power supply capable of 6 components
- Cleanest power using non-switching power supply
- 5 Box Design component & 1 turntable power output
- Not suitable for integrated & power amplifiers
- Soft-start-system: no current-inrush
- Audio type toroidal transformer
- Main isolating transformer with copper foil shielding
- Voltage rectification with precise regulation
- High filtration capacity (10.000  $\mu$ F)
- Low ESR capacitors
- Low noise components with surge protection
- Rigid aluminium casing protects against interference
- Available in black or silver
- Magnetic wooden side panels available separately
- Made in Europe

**Input power:** 115V/230V AC

**Output voltage / current (socket diameter):**

2 x 9V / 2A max (1,3mm);

3 x 18V / 1A max (2.5mm);

1 x 15V / DC-turntable (2.1mm)

**Filtration capacity:** 10.000  $\mu$ F

**Output voltage ripple:** < 1mV

**Trigger output:** 2,5mm jack

**Dimensions W x H x D:** 206 x 71 x 209 mm (with sockets)

**Weight:** 3000g

## Cleanest power for ultimate sound!

It is a proven fact that a power supply is a very important part of the audio path and significantly contributes to the sonic quality of an audio product. In order to offer the possibility of improving sound quality, we designed our linear power supply Power Box DS3 Sources. It significantly enhances the sound quality of up to six Box Design components, like streamers, CD players, pre-amplifiers and also offers the possibility to connect a DC-driven turntable.

A linear power supply consists of a massive toroidal transformer with shielding between primary and secondary winding, which acts as an isolating transformer and avoids penetration of interferences from mains into the audio component. The built-in transformer has a much higher power reserve compared to the standard power adapter. It has very low output impedance and in combination with large filtration capability it can easily manage all power needs. Sound staging, darkness of silent backgrounds and small detail resolution will improve strongly and contribute to a far better overall performance of each component.

Six standard connection cables are included in delivery. Special highend shielded connection cables in these lengths are available on request: 0,82m, 1.23m, 1.85m.

### The following interconnect cables are supplied in box:

2 x 9V (1.3mm connector)

3 x 18V (2.5mm connector)

1 x 15V (2.1mm connector) – to connect a DC driven Pro-Ject Audio Systems turntable.\*

\*ATTENTION: NOT SUITABLE for the following turntables: X8, Xtension 9, Xtension 10, Xtension 12, RPM 9, RPM 10 and the models of Signature line, with high power consumption and a heavy, mass loaded, platter. For these turntables we recommend the **Power Box RS2 Phono** or **Power Box RS Uni TT**.

Higher end power cables **Connect it Power** with superior shielding and transmission are also available for Power Box DS3 Sources!



**Compatible with:**

**9V products:**

CD Box DC  
CD Box DS2 T  
CD Box S  
CD Box S2  
CD Box S3  
Dock Box S Digital  
MaiA CD  
Media Box S  
Remote Box S  
Stream Box DS  
Stream Box DS net  
Bluetooth Box E  
Bluetooth Box S  
DAC Box S FL  
DAC Box S USB  
Switch Box S  
Tuner Box S  
USB Box S+

**15V turntables:**

all DC driven 15V Pro-Ject turntables

**\*ATTENTION: NOT SUITABLE** for the following turntables: X8, Xtension 9, Xtension 10, Xtension 12, RPM 9, RPM 10 and the models of Signature line, with high power consumption and a heavy, mass loaded, platter. For these turntables we recommend the **Power Box RS2 Phono** or **Power Box RS Uni TT**.

**18V products:**

A/D Phono Box S  
AD Box S2 Phono  
BT Box E HD  
DAC Box DS  
DAC Box E  
Dock Box S Fi  
Head Box DS  
Head Box S  
Head Box S USB  
Optical Box E Phono  
Phono Box  
Phono Box DS  
Phono Box DS+  
Phono Box DS2  
Phono Box DS3 B  
Phono Box DS2 USB  
Phono Box E  
Phono Box E BT  
Phono Box E BT5  
Phono Box MM  
Phono Box S  
Phono Box S2  
Phono Box S3 B

Phono Box S2 Ultra  
Phono Box ultra 500  
Phono Box USB  
Phono Box USB V  
Pre Box S  
Pre Box DS  
Pre Box DS2 Analogue  
Record Box E  
Record Box USB  
Speed Box S  
Speed Box S2  
CD Box DS  
CD Box DS3  
DAC Box DS2 Ultra  
Head Box DS2 B  
MaiA pre  
Pre Box DS2 Digital  
Speed Box DS  
Stream Box S2 Ultra  
Stream Box DS+  
Tube Box DS  
Tube Box Ds2  
Tube Box S  
Tube Box S2  
Vinyl NRS Box S3

